

ENGINEERING DOCUMENTATION

Rotary Servo Motor

Dimensional & Integration Guide

DOCUMENT	REVISION / ISSUE	STATUS
DIG-ES-SM-A02-180D-T22NM-3500W-001	DRAFT-08 / 27 Aug 2026	Engineering Integration Reference

Integration Overview


Closed-loop rotary servo motor for specified motion axes. This guide supports mechanical mounting, shaft and coupling integration, feedback and brake planning, cable routing, thermal validation and staged commissioning.

Key Integration Facts


INTEGRATION ITEM	PUBLISHED VALUE
Rated Torque	22 Nm
Rated Speed	1500 rpm
Flange Size	180 mm

Product Structure & Views


These views present product structure, mounting interfaces and relevant integration geometry for this SKU.




Mechanical View 2



Mechanical View 4



Mechanical View 6



Mechanical View 7



VIEW	FIELD	VALUE
Mechanical View 2	Connector pin label 1-17	Pin 1-17
Mechanical View 4	PINS	Pin 1-6
Mechanical View 6	Encoder connector identification	17 pin encoder connector
	Motor connector identification	6 pin motor connector
	Mounting circle diameter	Diameter 200 ±0.15
	Keyway height	12
	Keyway length	65
	Keyway width	8
	Shaft step length	6
	Shaft keyway length	65
	Pilot diameter	Diameter 114.3 +0/-0.035
	Maximum body height	204 maximum
	Shaft diameter	Diameter 42 +0/-0.016
	Shaft extension length	79 ±0.1
	Threaded hole size and depth	M8 thread, depth 25
	Mounting through-hole count and diameter	4 holes, diameter 13
	End step length	17
	Hole pattern angular spacing	45 degrees
	Front axial length	84.5 ±1
	Motor body axial length	260 ±1.5
	Mounting hole center distance	2 directions, 180 center distance
	Mounting hole radial position	4 mm
Mechanical View 7	Intermittent operating curve starting torque	Intermittent curve point torque 60.5
	Intermittent operating curve torque point	Intermittent curve point torque 55
	Torque Scale	0-70 N·m
	Motor Speed Scale	0-3000 rpm
	Continuous Torque	24.2 N·m
	Continuous Torque at 1500 rpm	22 N·m at 1500 rpm
	Maximum Speed	2800 rpm
	Intermittent operating region	Intermittent operation region
	Continuous operating region	Continuous operation region
	Torque axis label	Torque T in N·m
	Speed axis label	Rotational speed n in rpm

Overall Dimensions and Mounting Interface

PARAMETER	PUBLISHED VALUE	UNIT
Flange Size	180	mm

- Confirm the mounting face, locating feature, shaft geometry, fastener engagement and removal clearance against the applicable exact-SKU drawing.
- Mount the motor on a flat, rigid interface and avoid using fasteners to pull a misaligned assembly into position.

Shaft, Coupling and Load Path

PARAMETER	PUBLISHED VALUE	UNIT
Rotor Inertia	82	kgcm ²

- Align the driven shaft and coupling before tightening; validate radial, axial and moment loads against applicable bearing-load data.
- Do not hammer, uncontrolled press-fit or transmit installation force through the motor bearings.

Electrical, Feedback and Brake Integration

PARAMETER	PUBLISHED VALUE	UNIT
Position Feedback Device	2500 PPR incremental encoder	

- Use only the current winding, feedback, brake and connector definitions for this exact SKU.
- Verify drive compatibility, polarity, current limits, feedback direction and brake sequencing before enabling torque.

Thermal, Duty and Environmental Conditions

PARAMETER	PUBLISHED VALUE	UNIT
Rated Torque	22	Nm
Operating Temperature	20 40	°C

- Validate winding and housing temperature under the installed duty cycle, ambient condition, mounting heat path and enclosure airflow.
- Published peak values are transient boundaries and must not be treated as continuous operating ratings.

Cable Routing, Grounding and EMC

PARAMETER	PUBLISHED VALUE	UNIT
Position Feedback Device	2500 PPR incremental encoder	

- Provide strain relief and bend radius through the full machine motion envelope.
- Separate motor power, brake and feedback wiring and terminate shields according to the specified system grounding architecture.

Commissioning and Motion Validation

PARAMETER	PUBLISHED VALUE	UNIT
Rated Speed	1500	rpm
Rated Torque	22	Nm

- Commission at low energy with the transmission unloaded or safely restrained, then confirm direction, feedback polarity, brake final integration, current limit and fault response.
- Validate the complete axis through intended acceleration, speed, load, stop and fault cycles during integration planning.

Integration Checklist

- | | |
|----|--|
| 01 | Confirm the exact SKU, 2D drawing and applicable wiring data. |
| 02 | Verify mounting, shaft, coupling, alignment, fasteners and removal clearance. |
| 03 | Validate radial and axial loads, inertia, acceleration and credible shock cases. |
| 04 | Confirm drive, winding, feedback, brake and connector compatibility. |
| 05 | Set current, speed, acceleration and thermal limits from the installed duty cycle. |
| 06 | Verify cable routing, shielding, grounding, strain relief and bend radius. |
| 07 | Commission at low energy before validating the full machine cycle. |

[View SKU Product Datasheet](#) [Request controlled 2D drawing](#) [Request controlled STEP review](#) [Request a Quote](#)

Engineering Use and Verification Notice

01. This Dimensional & Integration Guide applies only to EmbodyStack SKU ES-SM-A02-180D-T22NM-3500W-001 and is intended for dimensional evaluation and preliminary integration. It is not a applicable manufacturing drawing, wiring definition, application approval, machinery risk assessment, safety validation or integration planning document. Before design freeze, machining, wiring or energization, verify all dimensions, tolerances, mounting and locating features, load boundaries, electrical interfaces, thermal conditions, cabling, grounding, protection, commissioning and applicable regulatory requirements against the applicable EmbodyStack engineering data for this exact SKU. Where this guide and applicable product documentation differ, the applicable product documentation governs. Validate the complete installed system under intended duty cycles, loads, accelerations, environmental conditions and credible fault cases.